

Memory Options

The ControlLogix controller is available in different combinations of user memory. Use [Table 13](#) to determine which controller meets your memory requirements.

Table 13 - ControlLogix Controller Memory Options

Controller	Memory for Data and Logic	I/O	Back-up Memory
1756-L61	2 MB	478 KB	CompactFlash card ⁽¹⁾
1756-L62	4 MB		
1756-L63, 1756-L63XT	8 MB		
1756-L64	16 MB		
1756-L65	32 MB		
1756-L71	2 MB	0.98 MB (1006 KB)	SD card
1756-L72	4 MB		
1756-L73, 1756-L73XT	8 MB		
1756-L74	16 MB		
1756-L75	32 MB		
1756-L72EROM	4 MB		
1756-L73EROM	8 MB		

⁽¹⁾ These nonvolatile memory cards are optional and do not come with the controller.

IMPORTANT The 1756-L7x controllers ship with an SD card installed. We recommend that you leave the SD card installed, so if a fault occurs, diagnostic data is automatically written to the card and Rockwell Automation can use the data to troubleshoot the anomaly.

IMPORTANT We recommend that you use the SD cards available from Rockwell Automation (catalog numbers 1784-SD1 or 1784-SD2). While other SD cards can be used with the controller, Rockwell Automation has not tested the use of those cards with the controller. If you use an SD card other than those cards that are available from Rockwell Automation, you can experience data corruption or loss. Also, SD cards that are not provided by Rockwell Automation can have different industrial, environmental, and certification ratings as those cards that are available from Rockwell Automation and can have difficulty with survival in the same industrial environments as the industrially rated versions available from Rockwell Automation.

ControlLogix Controller Features

The ControlLogix controllers are part of the Logix 5000[®] family of controllers that are offered by Rockwell Automation. The sections that follow describe the differentiating features of the ControlLogix controllers.

System, Communication, and Programming Features

[Table 12](#) lists the system, communication, and programming features available with ControlLogix controllers.

Table 12 - ControlLogix Controller Features

Feature	1756-L61, 1756-L62, 1756-L63, 1756-L64, 1756-L65	1756-L71, 1756-L72, 1756-L73, 1756-L74, 1756-L75	1756-L72EROM, 1756-L73EROM
Controller tasks	<ul style="list-style-type: none"> 32 tasks 100 programs/task Event tasks: all event triggers 	<ul style="list-style-type: none"> 32 tasks 1000 programs/task starting in Logix Designer application version 24 and later 100 programs/task starting in Logix Designer application version 15 32 programs/task prior to Logix Designer application version 15 Event tasks: all event triggers 	
Communication ports	1 port - RS-232 serial	1 port - USB, 2.0 full-speed, Type B	
Communication options	<ul style="list-style-type: none"> EtherNet/IP ControlNet[®] DeviceNet Data Highway Plus[™] Remote I/O SynchLink[™] Third-party process and device networks 		EtherNet/IP
Serial port communication	<ul style="list-style-type: none"> ASCII DF1 full/half-duplex DF1 radio modem DH-485 Modbus via logic 	N/A	
Controller connections supported, max	250	500	
Network connections, per network module	<ul style="list-style-type: none"> 128 ControlNet (1756-CN2/B) 100 ControlNet (1756-CN2/A) 40 ControlNet (1756-CNB) 256 EtherNet/IP; 128 TCP (1756-EN2x) 128 EtherNet/IP; 64 TCP (1756-ENBT) 		256 EtherNet/IP; 128 TCP (1756-EN2x)
Controller redundancy	Full support except for motion applications		
Integrated motion	<ul style="list-style-type: none"> Integrated Motion on the EtherNet/IP network Sercos interface Analog options: <ul style="list-style-type: none"> Encoder input LDT input SSI input 		
Programming languages	<ul style="list-style-type: none"> Relay ladder Structured text Function block Sequential function chart (SFC) 		